LTI Laser Interface to Softree's RoadEng

for Windows

Quick Reference Guide



Overview



Softree's RoadEng is a Windows application serving the civil engineering industry. In addition to a full interface to conventional surveying equipment and GPS, it also supports the LaserTech TruPulse instruments.

Compatible products

- TruPulse 360/R
- RoadEng ver 8.x

Type of Laser Methods available in RoadEng

- Distance/Azimuth
 - Measure Slope Distance, Inclination & Azimuth

1. Using the Bluetooth Manager on your Windows device, connect your TruPulse laser and note the Outgoing COM port number assigned to it. In this case it is COM4

Home	Divoto oth		
	Bluetooth	🕰 other devices	
Find a set	8 Bluetooth Settings	× ith or other device	Turn on Bluetooth even faster
Devices	Options COM Ports Handware This PC is using the COM (serial) ports listed below. To determine whether you need a COM port, read the documentation that came with your Bluetooth device.		To turn on Bluetooth without opening Settings, open action center, and then select the Bluetooth icon. Do the same to turn it off when you want.
읍 Printer	COM3 Incoming TP360R8-000348 COM4 Outgoing TP360R8-000348 'Bluetooth Serial	s "SCOLBURN-NB2"	Get more info about Bluetooth
() Mouse		rd, & pen	Related settings
🗔 Touchi		1 Mouse X4000b	Devices and printers Sound settings
📼 Typing			Display settings
		9 8 Series (65)	More Bluetooth options
AutoP AutoP	Add Remove	ed 3 8 Series (65)	Send or receive files via Bluetooth
Ö USB	OK Cancel Apply	kd P TV stick eered	Have a question? Get help
			Make Windows better Give us feedback
	Generic P	nP Monitor	
	Magali's 2 Not conne	end Fire TV stick ected	
	 Blueto Printer Mouse Touch Toping Pen & AutoP 	Devices The PC is using the COM (serial) ports linted below. To determine whether you need a COM port, read the commentation that can eve with your Blockhold below. To Devices Blueto Printer O Mouse Touch Typing P Pen & O AutoP Add_ Remove USB OC Const Apply Com Const Con	Devices Tis RC is using the COM (serial) ports listed below. To definition whether you used a COM out read the difference whether you used a COM o

60		800	Ba) #		Survey-Map	52	٥	>
-	Home	View	GPS/Laser	Setup				
New Travers	40	Quick Map		C Anchor Mode Polar / Delta Mode Measurement				

2. Start the RoadEng program on your Windows device and from the Home tab, click on New Traverse

3. Establish your Starting Coordinate by either entering XYZ values or set it from GPS (If connected, refer to manual for instructions)

🗟 🗖 🖻 🚔 🚔 🕴 🗧 Survey/Map -

	а 1	Survey/Map	- 0
Home View G	PS/Later Setup		
~~ B III	C Anchor Mode		
New New Quick Traverse Map Map	A Polar / Delta Mode		
Create	Measurement		
		Starting Coordinate ×	
		Easting X	
		Northing Y: 00	
		Elevation Z: 100 0	
		Setton GPS 📓 🖸	
		OK	
			508946
		- o ×	

4. With the Traverse sheet open, click on the GPS/Laser tab along the top

5. Click on the Connect Laser button

		5 & &) =	Survey/N	Map - [verse					
🙂 н	lome	View GPS	/Laser S	Setup Tra	verse					
0	Ø	Diptions Status	Latitude			Sample Copy Point				
Connect C	lose C	Options Status	Longitud	ie		Sample Copy Conn	ect Close Scroll			
Se	ttings			Status		Point Waypoint La	ser Gun Views			
		Fore Azim			Slp.(%)			GND	CRK	Label
	ťΤ									
								_		
								_		
								_		
	\vdash								<u> </u>	
	\vdash			<u> </u>					-	
	\vdash							-	-	
	+							-	-	
				<u> </u>				-		
								_		
	FS				0	0/				
× 0.0						w	0/	**		
<										

83 2	S/Laser Setup		/ 6 6	2 🖬 🚮			
Options State	IS Elevation		Sample Copy Conn	ect Close Scroll			
	Stat	JS	Vaypoint La	iser Gun Views			
Fore Azim	H.D.	i.D. Slp.(%)	SSL Sip.(%)/S.D.	SSR SIp.(%)/S.D.	GND	RK Label	
						Serial Settings ×	
					-	Com Porti a	
					-	Baud Rate: 4800 V	
					+	Advanced	
-					-		
					+	Size: 8 V	
					+	Handshake Xon/Xoff 🗸	
					+		
					+		
					+	Press F1 for Help	
						OK Carel	
					-		
					-		
			or	0/	**		
			Extent Extent . Fore Azim H.D. S.D. Sip.(H)	Statu Wagetet La Fore Acim H.D. S.D. Sip.(A) SSL Sip.(A) </td <td>Statu Waynowith Lawr Curt Years - Fore Azim H.D. S.D. Sip.(p) Sist Sip.(p)/SiD. SSR Sip.(p)/SiD. </td> <td>Stata Weyneth Law Car. Weyneth - Fore Acim H.D. S.D. Sip, (2) SSR Sip, (2)/S.D. SSR Sip, (2)/S.D.<td>Stria Wagent Law for Wagent Label Fore Adm H.D. S.D. Sip(5) Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sit Sip(5)S.D. Sit Sit Sit Sit Sit Sit Sit Sit Sit Sit</td></td>	Statu Waynowith Lawr Curt Years - Fore Azim H.D. S.D. Sip.(p) Sist Sip.(p)/SiD. SSR Sip.(p)/SiD.	Stata Weyneth Law Car. Weyneth - Fore Acim H.D. S.D. Sip, (2) SSR Sip, (2)/S.D. SSR Sip, (2)/S.D. <td>Stria Wagent Law for Wagent Label Fore Adm H.D. S.D. Sip(5) Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sit Sip(5)S.D. Sit Sit Sit Sit Sit Sit Sit Sit Sit Sit</td>	Stria Wagent Law for Wagent Label Fore Adm H.D. S.D. Sip(5) Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sip(5)S.D. Sit Sit Sit Sip(5)S.D. Sit

6. Select the Com Port number for the laser from the list, ensure the parameters are set as shown and tap OK

7. A window will appear announcing success in connecting to the laser. Tap OK

		View GP	Survey/1	Map - [.	verse											-	. 0
nect Cir	ose Op	ations Statu	Latitude Longitu Elevatio	de		Sample Copy Point Waypoint	nect Close	Scroll Lock									
		Fore Azim			Sin (%)				GNE	CRK	Label						
	.,				0.0.00	ooc opproprior		(0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,									
							-			-							
_							-										
_							-		survey			×					
_	\vdash			<u> </u>													
-							+		- <u>A</u>	TP360	MAIN-3.28: Port opened successfully						
-							-										
							-				ОК						
									_			_					
							-			<u> </u>							
									_								
	\vdash								_								
_							-		_	-							
-			-				-		-	-							
			-				-										
	FS				0												
0.0						0/	0/		**								
														-	A A .	h	
															2 I 6		

Taking Shots with the Laser

8. To measure a Side Shot, place the cursor at the bottom of the SS Column

			lap - [-	
	View GPS	/Laser S	ietup Tra	werse												
80	\square		<⊅ Anch	or Mode												
lew Q	luick		△ Polar	/ Delta Mo	de											
Map M reate	Map	Me	asurement													
				Slp.(%)	SSL SIp.(%)/S.D.	SSR SIp.(%)/S.D.	GND	CRK	Label							
ŕ											1					
+							-				1					
-							-				1					
											1					
											1					
										_						
							-			-						
\vdash							-			-	-					
				-			-			-	-					
							-				-					
							-			-	-					
\vdash		_		-			-			-	-					
+							-			-	-					
+				-			-			-	-					
+							-				1					
											1					
FS				0												
					0/	0/	нн				1					

Home View GPS/Laser Setup Traverse	
Home View GPS/Laser Setup Traverse	_ = x
Connect Close Options Status Bevation Status	Convect Cose Convect Cose Convect Cose C
Station Ty Fore Azim H.D. S.D. Sip.(%)	SL Stp (24)/S.D. SSR Stp. (24)/S.D. GND CRK Label
	Image: Section of the sectio
FS 0	
» 0.0 0	Q(##
¢	

9. Aim at the Side target and Fire the Laser. A window will appear showing the point number and measurement data. Choose SS for the Shot Type, Input a Code for the point and tap Enter Shot.

Taking Shots with the Laser

10. The data will appear in the appropriate cell on the Traverse Sheet

	000										
	Home V	ew GPS	Laser S	etup Tra	werse			-			
),	Orse Optic	> 🌠	Latitude			/ 🔓 🖸	2 🖬 🕻	3			
onnect (Close Optic	ns Status	Elevation			Sample Copy Conr Point	nect Close	icroll .ock			
	ettings					Waypoint La					
station	Ty Fo	re Azım	H.D.	5.D.	SID.(%)	SSL SIp.(%)/S.D.	SSR SIP.	.[%]/S.D.	GND	CRK	Label
	++										
	++										
					-						
	++										
	++										
					-						
	++										
	++										
0.	FS				0		0/				
0.	0					0144.0,07.1	07		**		
()											

		ean_) ∓ Surv	ey/Map - [Setup T									- 1	
ect Clo	ose Options	Status Elev	gitude ation	raverse	Sample Copy Point	Connect Close Laser Gun							
			Status	01- (80	Waypoint	SSR Slp.(%)/S.D.	010	CRK	Label	_			
uon	Ty Fore	Azim ri.i). S.D.	SID.[%]	55L SID.(%#5.D.	55R SIP.(%)/5.0	GND	CRK	Label	-			
-	_									-			
-	_			++				\vdash		-			
							-						
_	_	_	_				_			-			
_	_		_				_			-			
-	_		_							-			
-	_	_								-			
-	_	_								-			
-	_									-			
										1			
	_		_										
_	_	_	_				-			-			
-	_	_	-				-			-			
-	FS	-		0		_	-			-			
0.0				-	/44.0,0/	0/	**						
											= -		>

11. To take a Fore shot, place the cursor in the Fore shot column

Taking Shots with the Laser

12. Aim at the Fore target and Fire the Laser. A window will appear showing the point number and measurement data. Choose ForeShot for the Shot Type, input a Code for the point and tap Enter Shot.

*Note: if using a TruPulse 200 model, the Azimuth can be measured and input manually

opend At 0.0	× 1ap - [. Towerse						- 0
	Setup Traverse						- 1
Shot Type ForeShot Horizontal Angle BackShot Vertical Angle SSR IFS	je	Sample Copy Point Waypoint	nnect Close Scroll Lock				
Slope Distance SSR JPS Side Shot Code SSL JFS SSL JFS	S.D. Slp.	(%) SSL SIp.(%)/S.D.	SSR SIp.(%)/S.D.	GND	CRK	Label	
Insert At 0.0 e next trigger-press on the laser gun w				-			
tornatically accept this data				-			
Enter Shot Cancel				-			
Curcer							
				-			
				_			
				-			
				-			
	_			-			
	_	_		-			
	_			-			
FS		0		-			
0.0		8/44.0,20/57.0,3/	0/	**			
0.0		Gran. 6, 2, 6, 37, 0, 38.	W	**			

R	68	188) :	Survey/M	ap - [🗆 🕫	verse							
Эн	ome	View GPS/	/Laser 5	etup Tra	verse							
onnect C	ose Op	ptions Status	Latitude Longitud Elevation	e		Sample Copy Point Waypoint	hect Close Scroll Lock aser Gun Views					
		Fore Azim			Slp.(%)	SSL SIp.(%)/S.D.	SSR SIp.(%)/S.D.	GND	CRK	Label		
											1	
								-				
1											1	
											-	
								-			-	
	\vdash							-	-		4	
	\vdash							-	-		-	
_			_					-			-	
_								-			-	
	FS				0			-	-		-	
31.8	1.0					0/	0/	**			-	
	FS	20.3	31.8	32.0				<u> </u>				
0.0						8/44.0,20/57.0,3/	0/	**			-	
								1			-	
												$\textcircled{1} \square \blacksquare \bigcirc \textcircled{1} \textcircled{2} \textcircled{1}$

13. The data will appear in the appropriate cell on the Traverse Sheet. Continue in this manner to collect the survey data. Tap Close in the Laser toolbar at the top of the screen to close connection with the laser.

Product Resources

Product Page/User's Guides:

https://www.lasertech.com/TruPulse-Laser-Rangefinder.aspx

https://www.softree.com/roadeng-8



Stay informed! Find out about Laser Technology products, updates, and training resources by keeping track of us on FaceBook (/LaserTechnologyInc), Twitter (@LaserTechPro) and YouTube (/user/LaserTechPro)

Contact Laser Technology, Inc.

Questions regarding the interface to RoadEng or our laser products?

Please contact us at:

1.800.280.6113 or 1.303.649.1000

info@lasertech.com

Laser Technology, Inc. 6912 S. Quentin St. Centennial, CO 80112

www.lasertech.com



BLATER TECHNOLOGY